

Meter Mod III

Main Breaker Modules

Single-Phase and Three-Phase w/ Integral Pull Box

Main Breaker Module with Integral Pull Box (Single and Three-Phase) - EUSERC Unit

For EUSERC applications please check with local utility requirements to make sure the pull box meets their dimensional requirements. Some applications may require you to use a Commercial Metering Switchboard.

Main Breaker Module with Integral Pull Box Single-Phase- EUSERC Unit

Product Number	Main Ampere Rating	IC Rating	Feed Location	Main Frame Type	Line/Main Lug Size	Line/Main Neutral Size
TMPBU4R	400	65	Top / Bottom	SGH	Landing Pads Only ¹	Landing Pads Only ¹
TMPBU6R	600					
TMPBU8R	800					
TMPBU10R	1000			SKH		
TMPBU12R	1200					

¹Landing pads with 1/2" bolts per EUSERC drawing number 347 provided. Contractor will need to supply crimp/compression lugs.

Main Breaker Module with Integral Pull Box Three-Phase - EUSERC Unit

Product Number	Main Ampere Rating	IC Rating	Feed Location	Main Frame Type	Line/Main Lug Size	Line/Main Neutral Size
TMP3BU4R	400	65	Top / Bottom	SGH	Landing Pads Only ¹	Landing Pads Only ¹
TMP3BU6R	600					
TMP3BU8R	800					
TMP3BU10R	1000			SKH		
TMP3BU12R	1200					

¹Landing pads with 1/2" bolts per EUSERC drawing number 347 provided. Contractor will need to supply crimp/compression lugs.

Main Breaker Module Accessories

Main Breaker Modules Alternate Rating Plugs—Field installed

Breaker Frame Rating (Amps)	Trip Rating (Amps)	Rating Plug Product Number
400A	225	SRPG400A225
	250	SRPG400A250
	300	SRPG400A300
	350	SRPG400A350
600A	250	SRPG600A250
	300	SRPG600A300
	350	SRPG600A350
	400	SRPG600A400
	450	SRPG600A450
800A	500	SRPG600A500
	300	SRPK800A300
	400	SRPK800A400
	500	SRPK800A500
	600	SRPK800A600
1200	700	SRPK800A700
	600	SRPK1200A600
	700	SRPK1200A700
	800	SRPK1200A800
	900	SRPK1200A900
	1000	SRPK1200A1000
	1175	SRPK1200A1175

Shunt Trip—Field Installed

For use on all Main Breaker Modules

Shunt Trip	Product Number
120 Vac	SAST1
240 Vac	SAST2