

MOTICAMS12

USB CAMERAS

The new Motic sCMOS cameras developed by German engineering represents a new impetus to manufacturing quality, technical precision and lightweight design. With a member of this line the door for new application fields opens wide. The accelerated data readout (Global Shutter) also enables to work on fast moving phenomena.

If it is about maximum resolution for printing purposes, Moticam S12 is your choice. A 25fps maximum frame rate manages the largest data volume of Motics S Series. If resolution in display or for printing is in your mind, Moticam S12 is your solution.



www.moticamseries.com | moticroscopes.com

SCIENTIFIC CMOS CAMERA





MOTICAM S12 TECHNICAL SPECIFICATIONS

Sensor type	sCMOS
Sensor size	1/1.7"
Imaging area	9.33mm (Diagonal)
Capture resolution	12MP
Live display mode through USB	4000x3000, 2048x1080 pixels
Pixel size	1.85x1.85µm
Scan mode	Progressive
Shutter mode	Rolling Shutter
Data transfer	USB 3.1
Max. frames per second (fps*)	4000x3000 @ 25fps, 2048x1080 @ 50fps (*)
Exposure time	22 µsec to 2 sec
Operating temperature	From -10 to +60 Degrees Celsius non condensing
Sensitivity	280mV(G) @ 1/30 sec
Support device	TWAIN, SDK and DirectShow Driver
Supported OS	Microsoft Windows 7/8/10, MAC OSX10.9, Linux or higher
Minimum computer requirements	2GHz dualcore - RAM memory 2GB - Video memory min. 512 MB
Lens mount	C-Mount
Software	Motic Images Plus 3.0 for Windows, OSX and Linux
Functions	Still image and video capture, live and still image measurement, image adjustments, white balance, automatic & manual exposure, individual objective calibration system.
Power supply	5V (from USB Port)
Package includes	CS ring adaptor, USB 3.1 cable, Motic 4-dot calibration slide, Motic Images Plus 3.0 for PC/OSX/Linux


**Frames per second under optimal lighting conditions and in compliance with computer technical requirements.*

MOTIC IMAGES PLUS 3.0 IMAGE ANALYSIS SOFTWARE

Grab your image with highest sensor sensitivity. Navigate in the dark!

Motic Images Plus 3.0

By connecting your Moticam to your computer you will be able to work with our well-known software that comes included in the package. View, capture, edit, measure, make reports... all its standard features and the new ones packed in a new user-friendly interface.



FAST FRAME RATES



sCMOS SENSOR



USB 3.1 INTERFACE



MIP 3.0 SOFTWARE