Single Position Lever Bypass

200 Amps | 7 Terminals | Ringless | 600 VAC



U9700-RRL




U9701-RXL-ALT




U1493-X-ALT




U4910-O-BL-ALT




9700



9701



1493



4910

Alliant Approved | 200 Amps | Lever Bypass | 600 VAC

Catalog Number	Terminals	Service	Hub	Connectors CU/AL		Dimensions			Knockouts				
				Line	Load	D"	W"	H"	1	2	3	4	5
U9700-RRL	7	OH	H.O.	#6-350	#6-350	4 27/32	10	18½	3	2½	¾	¼,½	—
U9701-RXL-ALT	7	OH	C.P.	#6-350*	#6-350	4 27/32	13	19	3	2½	¼,½	¼	—
U1493-X-ALT	7	OH/UG	C.P.	#6-350	#6-350	6	18	19¼	4	3½	2½	¼,½	—
U4910-O-BL-ALT	7	UG	Blank	#6-350	#6-350	5¾	16	22	4	3½	2½	1	¼

MidAmerican Approved | 200 Amps | Lever Bypass | 600 VAC

Catalog Number	Terminals	Service	Hub	Connectors CU/AL		Dimensions			Knockouts			
				Line	Load	D"	W"	H"	1	2	3	4
U9700-RRL	7	OH	H.O.	#6-350	#6-350	4 27/32	10	18½	3	2½	¾	¼,½
U9701-RXL	7	OH/UG	C.P.	#6-350	#6-350	4 27/32	13	19	3	2½	¼,½	¼

Notes

- **Hubs:** For proper hub selection, see the hub suffix chart on the accessories page.
- **Connectors:** Extruded aluminum connectors are tin plated.
- **Bypass:** Lever supplies clamping action on meter spades and also operates bypass device.

Please consult serving utility for their requirements prior to ordering or installing, as specifications and approvals vary by utility, and may require local electrical inspector approval. All installations must be installed by a licensed electrician and must comply with all national and local codes, laws and regulations. Milbank reserves the right to make changes in specifications and features shown without notice or obligation.