



SPECIFICATION

| | |
|---------------------------|--|
| Model Name | X470 GAMING PLUS MAX |
| CPU Support | Supports 1st, 2nd and 3rd Gen AMD Ryzen™ / Ryzen™ with Radeon™ Vega Graphics and 2nd Gen AMD Ryzen™ with Radeon™ Graphics / Athlon™ with Radeon™ Vega Graphics Desktop Processors for Socket AM4 |
| CPU Socket | Socket AM4 |
| Chipset | AMD® X470 Chipset |
| Graphics Interface | 2 x PCI-E 3.0 x16 slots + 1 x PCI-E 2.0 x16 slot Supports 3-way CrossFire |
| Display Interface | HDMI, DVI-D - Requires Processor Graphics |
| Memory Support | 4 DIMMs, Dual Channel DDR4-3866+(OC) |
| Expansion Slots | 3 x PCI-E x1 slots |
| Storage | 2 x M.2 slots, 6 x SATA 6Gb/s |
| USB Ports | 2 x USB 3.2(Gen2) + 8 x USB 3.2(Gen1) + 6 x USB 2.0 |
| LAN | Realtek® 8111H Gigabit LAN |
| Audio | 8-Channel(7.1) HD Audio with Audio Boost |

CONNECTIONS



1. PS/2 Combo Port
2. USB 3.2 Gen1
3. LAN Port
4. HD Audio Connectors
5. USB 2.0 Ports
6. DVI-D Port
7. HDMI Port
8. USB 3.2 Gen1
9. USB 3.2 Gen2
10. Optical S/PDIF OUT

FEATURE



Turbo M.2

Running at PCI-E Gen3 x4 maximizes performance for NVMe based SSDs.



Audio Boost

Reward your ears with studio grade sound quality for the most immersive audio experience.



8+4 Pin power supply

By providing 8+4 pin connectors to ensure adequate power supply to unleash ultimate multi-core CPU performance.



Core Boost

With premium layout and fully digital power design to support more cores and provide better performance.



Mystic Light RGB

Personalize your PC with 7 colors / 7 effects controlled in one click with MYSTIC LIGHT APP or a mobile device.



DDR4 Boost

Advanced technology to deliver pure data signals for the best gaming performance and stability.



EZ Debug LED

Easiest way to troubleshoot.